
Introduction

The TA131 is a passive high impedance probe, designed for use with oscilloscopes. It is calibrated to work effectively with instruments that have an input impedance of 1M Ohm. shunted by 18 pF. You can also use it with oscilloscopes that have an input capacitance of 10-35pF, if you make an adjustment to compensate. In the head of the probe is a two position slide switch which allows you to select the attenuation you require: either X1or X10. The small box adjacent to the BNC plug contains two adjustable resistors that enable high frequency trimming. This is usually not required.

Frequency compensation adjustment

Connect the probe to an oscilloscope and a 1KHz square waveform source. Move the attenuation switch on the probe to the X10 position. Set the oscilloscope to display two to three cycles, and two to six vertical divisions. Carefully adjust the compensation trimmer tool on the head of the probe until the waves displayed on the oscilloscope are perfectly square.





Pico Technology Ltd

Tel +44 (0)1480 396395 Fax +44 (0)1480 396395 www.picotech.com E-mail: sales@picotech.com

Specifications:

Position X10

Attenuation Ratio 10.1

Bandwidth DC to 250MHz

Rise time 1.4ns

Input Resistance 10M when used with

oscilloscopes with 1M input

Input Capacitance Approx.11pF 10 to 35pF

Compensation Range

600VDC incl. Peak AC Working Voltage

derating with frequency (see Fig. 1)

Position X1

Attenuation Ratio 1:1

DC to 10MHz Bandwidth

Rise Time 35ns

Input Resistance 1M(Oscilloscope Input) Input Capacitance 46pF plus oscilloscope

capacitance


Working Voltage

600V DC incl. Peak AC Derating with frequency

Safety conformed IEC-1010 CAT II

Cable Length 1.2Meter

Voltage derating curve



Update:22-04-2011